Siemens 6ES7314-1AG14-0AB0 SIMATIC S7-300 CPU 314



Siemens 6ES7314-1AG14-0AB0 is the SIMATIC S7-300 CPU 314 for a modular rack whose field channels are provided by selected signal modules.

Technical Specifications

Product Identity	
Manufacturer	Siemens AG
Complete order number	6ES7314-1AG14-0AB0
Product family	SIMATIC S7-300
CPU designation	CPU 314
Functional Configuration	
Communications	MPI
Signal arrangement	Modular signal I/O
Housing (W × H × D)	40 × 125 × 130 mm
Performance & Power	
Integrated work memory	128 KB
Rated supply	24 V DC
Permissible supply range	19.2–28.8 V DC
Environment	
Operating ambient temperature	0–60 °C, subject to the mounting conditions of the system

Celine | unity@mvme.cn | +86-18020776786

Compatibility & Selection Guide

Configure this order variant as CPU 314 in the S7-300 hardware project. Siemens lists STEP 7 V5.5 SP1 or V5.2 SP1 with HSP 218 for its engineering environment. An applicable SIMATIC Micro Memory Card is required for load memory.

Wiring & Installation

Separate S7-300 signal modules carry the field wiring. Keep the CPU supply within 19.2–28.8 V DC. Use the documented SIMATIC S7-300 mounting and connection procedures for the installed rack.

Frequently Asked Questions

How large a Micro Memory Card can 6ES7314-1AG14-0AB0 use?

It accepts a SIMATIC Micro Memory Card up to 8 MB as load memory.

How much retentive data can 6ES7314-1AG14-0AB0 preserve on a power interruption?

The maximum retentive data area is 64 KB. Allocate the values that must survive a power interruption within that limit.

How many diagnostic events can 6ES7314-1AG14-0AB0 retain for fault finding?

The diagnostic buffer has up to 500 entries, with the last 100 entries retained after power loss.

How long does the real-time clock of 6ES7314-1AG14-0AB0 keep time without power?

Clock backup time is six weeks at an ambient temperature of 40 °C.

How many S7-300 racks can 6ES7314-1AG14-0AB0 address in one local assembly?

The configuration supports up to four racks in total, including the central rack.

What block-count limit should a project migration to 6ES7314-1AG14-0AB0 allow for?

The CPU supports up to 1,024 DBs, FCs and FBs combined. The selected memory card can reduce the number that can actually be loaded.

How many connections can be allocated to programming devices on 6ES7314-1AG14-0AB0?

The configurable allocation for PG communication is 1 to 11 connections.

Which startup organization block can 6ES7314-1AG14-0AB0 execute?

Startup logic runs in OB 100. The CPU supports one startup organization block.

Source: Siemens exact-order datasheet. Selected manufacturer page follows.

SIEMENS

Data sheet 6ES7314-1AG14-0AB0



Figure similar

SIMATIC S7-300, CPU 314 Central processing unit with MPI, Integr. power supply 24 V DC, work memory 128 KB, Micro Memory Card required

General information	
Engineering with	
● Programming package	STEP 7 V5.5 + SP1 or higher or STEP 7 V5.2 + SP1 or higher with HSP 218
Supply voltage	
Rated value (DC)	24 V
permissible range, lower limit (DC)	19.2 V
permissible range, upper limit (DC)	28.8 V
external protection for power supply lines (recommendation)	2 A min.
Mains buffering	
● Mains/voltage failure stored energy time	5 ms
● Repeat rate, min.	1 s
Input current	
Current consumption (rated value)	650 mA
Current consumption (in no-load operation), typ.	140 mA
Inrush current, typ.	3.5 A
I^2t	1 $A^2 \cdot s$
Power loss	
Power loss, typ.	4 W
Memory	
Work memory	
● integrated	128 kbyte
● expandable	No
● Size of retentive memory for retentive data blocks	64 kbyte
Load memory	
● Plug-in (MMC)	Yes
● Plug-in (MMC), max.	8 Mbyte
● Data management on MMC (after last programming), min.	10 y
Backup	
● present	Yes; Guaranteed by MMC (maintenance-free)
● without battery	Yes
CPU processing times	
for bit operations, typ.	0.06 µs
for word operations, typ.	0.12 µs
for fixed point arithmetic, typ.	0.16 µs

Subject to change without notice
© Copyright Siemens