Honeywell 8C-PAOHA1 51454469-275

16-Channel HART Analog Output Module

Honeywell 8C-PAOHA1 51454469-275 is the Series 8 HART analog output module for applications that need sixteen 4–20 mA control outputs. It supplies constant-current signals to actuators and recording or indicating devices. This is the HART-capable output model; Honeywell separately lists 8C-PAONA1 for analog output without HART.



Technical Specifications

Product Identity	
Manufacturer	Honeywell
Complete part number	8C-PAOHA1 51454469-275
Product family	Series 8 I/O
Functional Configuration	
I/O function	HART analog output
Output channels	16
Nominal output	4–20 mA
Directly settable output range	2.9–21.1 mA
Redundancy switchover gap	10 ms maximum at 0 mA; redundant configuration only
Nonredundant IOTA	8C-TAOXA1, coated, 6 in
Redundant IOTA	8C-TAOXB1, coated, 12 in
Performance & Power	
Voltage rating	24 VDC
Module current rating	205 mA
Load resistance	50–800 Ω with a 22–28 VDC supply
Calibrated accuracy	±0.2% of full scale at 25°C, including linearity
Maximum compliant output voltage	16 V with a 22–28 VDC supply
Output response	Within 1% of final value in 80 ms
Environment	
Protection of electronics	Conformal coating

Selected original manufacturer material follows on pages 3–8.

Compatibility & Selection Guide

System compatibility. The 8C-PAOHA1 is documented in Honeywell’s Series 8 I/O and C300 controller platform. It supports HART-capable multivariable devices, open-wire detection and optional redundancy. Each channel can hold its last value or move to a configured safe value through FAILOPT; an IOM electronics failure instead forces the output to zero. Select this model when the existing application requires HART output functionality and confirm the installed Series 8 configuration before replacement.

Wiring & Installation Reference

Field connection checks

The module plugs onto its IOTA, where the field terminals and power distribution are located. Confirm the installed termination assembly before moving wiring.

IOTA and configuration

Match the termination assembly. Use the documented 8C-TAOXA1 nonredundant IOTA or 8C-TAOXB1 redundant IOTA. The IOM plugs onto the IOTA; field terminations remain on that assembly.

Check the output loop. Check the load against the specified 50–800 Ω range at 22–28 VDC. Honeywell lists 16 V maximum compliant output voltage under these supply conditions.

Review the configured safe state. Check each channel’s FAILOPT selection and configured safe value. An IOM electronics failure forces the output to zero regardless of hold-last-value configuration.

Installation precautions. A redundant switchover can produce a gap of up to 10 ms at zero output current; check the connected process device’s requirements. Honeywell’s Series 8 environmental limits are tied to the specified cabinet conditions. The reference distinguishes 0–50°C external ambient from 0–60°C internal ambient and includes humidity derating above 40°C.

View field connection reference (PDF) · PDF page 7 | View IOTA installation reference (PDF) · PDF page 4

Manufacturer sources: Honeywell Series 8 Controller and I/O Specification — model-specific specification / Honeywell Series 8 Controller and I/O Specification — platform, field connections and IOTA selection / Honeywell Series 8 Controller and I/O Specification — module and IOTA function matrix.

2. Platform Environmental Specifications

2.1. General Environmental Characteristics

This section relates to the physical characteristics applicable to Series 8 C300 controller and all Series 8 I/O components. Where applicable, specifications state limits within an approved cabinet and to the cabinet skin.

Consideration	Operating Limit [1]	Transportation and Storage Limits [1a]
Ambient Temp Range	External: 0 to 50°C [2] Internal : 0 to 60°C [3]	-40 to 85°C
Temp. Rate of Change	<= 1°C/min	<=5°C/min
Relative Humidity [3]	5 to 95% (non-condensing) [4]	5 to 95% (non-condensing) [4]
Barometric Pressure Altitude	-300 to +3000 m	Any
Corrosives	G3 Standard (ISA S71.04) - Denoted by “8C-“ model number in this doc	G3 Standard (ISA S71.04) - Denoted by “8C-“ model number in this doc
Vibration (3 axes)	Sinusoidal (5 to 10 Hz) 2.54mm/0.100in Max (10 to 150 Hz) 0.5 g max. (0-Pk)	Random Vertical Shipping Axis 5 to 300 Hz 1.07 g (rms) Longitudinal and Transverse 10 to 500 Hz, 0.74 g (rms) 60 Minutes each axis
Mechanical Shock (3 Axes)	Site Induced: Terminal Peak Sawtooth waveform 4g max. @25ms	N/A

Note 1 – Operating Limits define the range of operating conditions within which the system is designed to operate. Performance characteristics are defined when operating in this state. Please see ANSA/ISA D 51.1 Process Instrumentation Terminology for more information.

Note 1a – Transportation and Storage Limits define the range of conditions to which the system may be subjected without permanent damage to the equipment. Performance is not guaranteed in this state. Please see ANSA/ISA D 51.1 Process Instrumentation Terminology for more information.

Note 2 – This rating applies to the external ambient temperature of the Standard 2000mm enclosure with doors closed.

Note 3 – This rating applies to the internal ambient temperature of the Standard 2000mm enclosure with the doors closed. New version of the C300 controller(8C-PCNT05) and Memory Backup Assembly module (50182539-001) support an extended temperature range from 0°C to 70°C.

Note 4 – The maximum relative humidity spec applies up to 40°C. Above 40°C the RH spec is de-rated to 55% to maintain constant moisture content.

A note on the transportation of Batteries:

Some Government agencies have regulations that may prohibit air transport of Lithium Batteries.

4. Series 8 I/O Hardware

4.1. Overview and Features

Series 8 features an innovative design that supports enhanced heat management. This unique look provides a significant reduction in overall size for the equivalent function.

Both Series 8 IOM and IOTA are available with Conformal Coated feature. The term ‘Coated’ stands for hardware with conformal coating material applied to electronic circuitry for protection against moisture, dust, chemicals, and temperature extremes. Coated IOM and IOTA are recommended when electronics must withstand harsh environments and need to have added protection.

The unique features of the Series 8 I/O include:

- I/O Module and field terminations are combined in the same area. The I/O Module is plugged into the IOTA to eliminate the need for a separate chassis to hold the electronics assemblies
- Two level “detachable” terminals for landing the field wiring in the enclosure, providing easier plant installation and maintenance
- Field power can be supplied through the IOTA, with no need for extra power supplies and the associated craft wired marshalling
- Redundancy is available directly on the IOTA without any external cabling or redundancy control devices, by simply adding a second IOM to an IOTA
- The innovative styling is one of its unique features. This styling includes features to facilitate the effective use of control hardware in a systems environment. These features include:
    - Vertical mounting for more effective wiring since most field wiring applications require entry from the top or bottom of the systems cabinet
    - An “information circle” for a quick visual cue to draw the Maintenance Technician’s eye to important status information
    - “Tilted” design for effective heat management within the cabinet enclosure. Since Series C allows for a significant increase in cabinet density, an effective heat management system is critical for high systems availability
    - Input and output circuits are protected from shorts to alleviate the need for in-line fusing, reducing installation and maintenance costs

Series 8 IOTAs combine multiple functions into a single piece of equipment:

- Single and redundant configurations
- On-board termination of process signals
- On-board signal conditioning
- On-board connection to appropriate networks (FTE, I/O LINK)
- Field power distribution without external marshalling
- IOM plugs into the IOTA and receives power from the IOTA
- The IOTA receives its power through cables from header board



4.2. I/O Module Functions

- **High Level Analog Input /HART Input Module (16pt) –** The High Level Analog Input Module supports both high level analog and HART inputs. Analog inputs are typically 4-20mA DC for both traditional and HART devices. HART data can be used for status and configuration. HART data, such as the secondary and tertiary variables, can also be used as process control variables. Two versions Single ended and Differential type are available.
- **High Level Analog Input w/o HART (16pt) –** The High Level Analog Input Module supports high level analog inputs Analog inputs are typically 4-20mA DC for traditional devices.
- **Analog Output/HART Output Module (16pt) –** The Analog Output Module supports both standard 4-20mA DC outputs and HART transmitter outputs.
- **Analog Output w/o HART (16pt) –** The Analog Output Module supports standard 4-20mA DC outputs.
- **Digital Input 24 VDC (32pt) –** Digital input sensing for 24V signals
- **Digital Input Sequence of Events (32pt) –** Accepts 24VDC discrete signals as discrete inputs. The inputs can be time tagged to support 1ms resolution Sequence of Events.
- **Digital Input Pulse Accumulation (32pt) –** Accepts 24VDC discrete signals as discrete inputs. The first 16 channels can be configured as Pulse accumulation to support Pulse Accumulation and frequency measurement on per channel basis. Channels 17 – 32 can be configured as DI.
- **Digital Output 24 VDC (32pt) –** Current sinking digital outputs. Outputs are electronically short-circuit protected.
- **DO Relay Extension Board (32pt) –** Digital output with NO or NC dry contacts. It can be used for low power or high power applications.
- **Low Level Analog Input – RTD & TC (16pt) –** Provides thermocouple (TC) and resistance temperature device (RTD) inputs.

4.3. Series 8 I/O Sizing

In virtually all configurations, the C300 controller and Series 8 I/O provides useful, maintainable process equipment connections in a smaller footprint than existing competitors and Honeywell equivalent products. Installing Series 8 I/O modules contributes to overall total installed cost savings.

IOTA sizes vary based on the application. In general, an analog module has 16 points and resides on a 6 inch (152mm) IOTA for non-redundant applications and a 12 inch (304mm) IOTA for redundant applications. A discrete module has 32 points and resides on a 9-inch (228mm) IOTA for non-redundant applications and a 12 inch (304mm) IOTA for redundant applications. Specific information on the size of a particular module is described in the Model Number Table.

4.3.1. Series 8 Field connections

Series 8 Field connections use a standard modular connector. The connector modularity allows for removal and insertion of the field wiring. This significantly reduces installation and maintenance procedures and can assist in field check out. Series 8 field connectors accept up to 12 AWG / 2.5 mm^2 stranded wire.

4.3.2. I/O Module Sizes

IOTA Sizing is nominal (6in = 152mm, 9in =228mm, 12in =304mm). I/O modules are associated with their respective IOTAs in the table below. The I/O Module is supported by one or more IOTAs. Below section also provides an overview of various available IO modules, IOTA, IOTA size and redundancy features.

I/O Module (Coated)	IOTA (Coated)	Description	Circuits	Size (in “)	Red.
8C-PAIH54		High-level AI HART, Differential	16		√
	8C-TAIDA1	AI IOTA		9	
	8C-TAIDB1	AI IOTA Redundant		12	√
8C-PAIHA1		High-level AI HART, Single-ended	16		√
8C-PAINA1		High-level AI w/o HART, Single-ended	16		√
	8C-TAIXA1	AI IOTA		6	
	8C-TAIXB1	AI IOTA Redundant		12	√
8C-PAIMA1		Low-level AI – RTD & TC	16		
	8C-TAIMA1	Low-level AI IOTA		9	
8C-PAOHA1		Analog Output HART	16		√
8C-PAONA1		Analog Output w/o HART	16		√
	8C-TAOXA1	AO IOTA		6	
	8C-TAOXB1	AO IOTA Redundant		12	√
8C-PDILA1		Digital Input 24V	32		√
8C-PDISA1		Digital Input Sequence of Events	32		√
8C-PDIPA1		Digital Input 24V Pulse Accumulation	32		√
	8C-TDILA1	DI 24V IOTA		9	
	8C-TDILB1	DI 24V IOTA Redundant		12	√
8C-PDODA1		DO 24V Bussed Out	32		√
	8C-TDODA1	DO 24V Bussed IOTA		9	
	8C-TDODB1	DO 24V Bussed IOTA Redundant		12	√
	8C-SDOX01	DO Relay Extension [1]		15	√

Note 1- DO Relay Extension board is used along with DO IO module with IOTA (Redundant or non-redundant). Refer Section 4.4.11 for more details.

4.4.5. Analog Output with HART

Function

The Analog Output (AO) Module delivers high-level constant current to actuators and recording/indicating devices.

Notable Features

- Extensive self-diagnostics
- Optional redundancy
- HART-capable, multivariable devices
- Safe-state (FAILOPT) behaviors configurable on a per channel basis

Safe-state Behavior (FAILOPT)

Series 8 AO module supports the FAILOPT parameter on a per channel basis. The user can configure each channel to either HOLD LAST VALUE, or SHED to a SAFE VALUE. The Output will always go to zero, the safe state, if the IOM device electronics fails.

Open-wire Detection

This Series 8 IO function can detect and annunciate open field wire with a Channel Soft Failure indication.

Detailed Specification- Analog Output with HART (8C-PAOHA1)

Parameter	Specification		
Input / Output Module	8C-PAOHA1 - Analog Output with HART, Coated		
IOTA Modules	8C-TAOXA1	Non-Redundant, Coated	6”
	8C-TAOXB1	Redundant, Coated	12”
Output Type	4-20 mA		
Output Channels	16		
Output Ripple	< 100 mV peak-to-peak at power line freq, across 250 Ω load		
Output Temperature Drift	0.005% of Full Scale/°C		
Output Current Linearity	± 0.05% of Full Scale nominal		
Load Resistance (24 V supply = 22 VDC through 28 VDC)	50-800Ω		
Voltage Rating	24 VDC		
Module current rating	205 mA		
Resolution	± 0.05% of Full Scale		
Calibrated Accuracy	± 0.2% of Full Scale (25oC) including linearity		
Directly Settable Output Current Range	2.9 mA to 21.1 mA		
Maximum Output Compliant Voltage (24 V supply = 22 VDC through 28 VDC)	16 V		

Parameter	Specification
Maximum Open Circuit Voltage	22 V
Response Time(DAC input code to output)	Settles to within 1% of final value within 80 ms
Gap (0 mA) of Output to Field on Switchover	10 ms maximum (applies to Redundancy only)
Module Removal and Insertion Under Power	Supported